

AMPLIDECT COMBI 595

Corded and Cordless Telephone with Large Photo Buttons and SOS buttons

CUNUX ET ON

-

VOL 6

1 2 3

4 5 6

7 8 9

¥ 0 #

De 12,00

GEEMARC

0328587599

Function to block up to 100 unwanted numbers!

CALLING/TALKING (Base)

- Hearing Aid Compatible
- → Adjustable receiving volume control (up to **50dB**)
- → 4 one-touch memories (with talking caller ID), 3 with pictures
- Speaker phone
- → Redial function for last 10 outgoing calls
- -> Phonebook can store up to 50 names and numbers (4 of which have talking caller ID)
- Mute/Pause function
- > Keyboard:
 - Large keys (25x14mm) 0
 - Big characters (10mm) 0

SOS BUTTONS (BASE + HANDSET)

- 1 SOS button: -
 - Save up to 4 emergency numbers 0
 - Recordable emergency voice message or existing text in 4 0 languages: English, French, German and Dutch

LCD DISPLAY (BASE + HANDSET)

- → Large screen (80*43mm-3 lines for the base / 40*34mm-2 lines for the handset)
- -White backlight
- -> Choice of 7 languages: English, German, French, Italian, Spanish, Dutch and Portuguese
- Navigation menu
- -> Time stamping
- > Alarm
- -Talk time indication

ANSWERING MACHINE

- -> 30 minutes of recording time
- -> On/Off key
- → 1 announcement
- -> 4-digit user selectable remote codes
- -> Remote control for messages on handset
- → Erase each/all messages
- -Time & date stamp on recorded messages
- 4 languages voice announcement: English, -German, French and Dutch
- -Voice memo recorder
- "Slow reading" function →
- → Choice of the number of ringtones before answering machine answers

MULTI HANDSET

- -> Handset locator
- -> Conference between the base and the handset
- → Up to 4 handsets
- -> Call transfer of external calls (when using several handsets)
- → Intercom between handset

RINGER

- → 10 ringtones for the base and 10 ringtones for the handset
- → Adjustable ring volume (Mute + 5 positions)
- → Visual ringer indicator on the base and on the handset
- → Adjustable ring volume up to 80dB on handset and base

AMPLIDECT 595 (Handset)

- Hearing aid compatible
- → Adjustable receiving volume: up to 50dB
- -> Adjustable speaker phone volume
- → 9 one-touch memories on the handset: Option to save telephone numbers on the 9 keys of the numeric keypad (1 to 9)
- -> Redial function for the last 10 outgoing calls on the handset
- -> DECT phone
- -> Memory storage
- -Power supply by DC adapter (supplied)
- → 3xAAA batteries ni-Mh 1.2V 600mA (included)
- → Standby time: 2 days
- → Continuous talk time: 10 hours
- -> Range:
 - Indoor: up to 50m 0
 - 0

VOICE ASSIST

- Talking caller ID for 4 memory buttons (names need to be recorded) ➔
- -Talking keys: voice assist for dialling numbers
- → 4 languages talking keypad: English, French, German and Dutch

TECHNICAL SPECIFICATIONS

- → 1 battery ni-Mh 2.4V 500mA (included)
- → Memory storage
- → Power supply by AC adapter (supplied)
- → Dial voice frequency
- → Main phone wall mountable
- -> GAP non-compliant
- -> Range:
 - Indoor: up to 50m 0
 - Open field: up to 300m 0

CALLER ID * (BASE)

- → Name presentation in hook mode (type 1) and conversation mode (type 2) 20 incoming numbers
- -> Talking keys: voice assist for dialling numbers
- -> Caller ID also for Call waiting
- → Indicator call waiting
- -> Indicator new call

ADDITIONAL HANDSETS

AMPLIDECT595 U.L.E AD



AMPLIDECT595 U.L.E AD



*To use the CID facility it will be necessary to subscribe to your network provider's CID service Items pictured and details are subject to change at the manufacturer's discretion.

- - Open field: up to 300m